DATA SHEET



MD 200 brown

Item number

GTIN

EM10025327

4015120025327

















230 V ~





Product description

- Motion detector with 200° field of detection for convenient light switching
- Sensing and range adjustment due to revolving and tilting spherical head technology

0.5 W

• Special bracket for mounting on inner and outer corners, available as accessory

Offers special product features like:

- One-hand plug-in base
- Zero-cross switching

Power consumption



Technical data

| r | Е | М | Е | D | ٨ | ı |
|---|---|---|---|---|---|---|
| u | C | N | C | ĸ | н | ı |

| Outdoor motion detector |
|---|
| Please note the Explanation of circuit breaker in the download area of the product! |
| Adjusting controller |
| _ |
| CE, EAC, RoHS, WEEE |
| 5 years |
| |

ATTACHMENT

| Installation type | Surface mounting |
|--------------------------------|------------------|
| Installation position | Wall |
| Type of connection | Push terminal |
| Connectable wire cross section | 1.50 — 2.50 mm² |

HOUSING

| Dimensions | Length 102 mm x Width 74 mm x Height/ Depth 81 mm |
|---------------------------------|--|
| Weight | 185 g |
| Material | UV-stabilised polycarbonate |
| Protection type | IP44 |
| Permissible ambient temperature | -25 °C+55 °C |
| Relative humidity | 5 - 95 %, non-condensing |
| Colour | brown, similar to RAL 8017 |

ELECTRICAL VERSION

| Control system | ON/OFF |
|------------------|----------------------------|
| Protection class | II |
| Nominal voltage | 230 – 230 V ~ / 50 – 50 Hz |
| In-rush current | 30 A / 20 ms |

| SENSORS | |
|---|--|
| Detection angle | 200° sensor horizontally rotatable +/- 90° |
| Detection range diagonally | Ø 20 m |
| Detection range head-on | Ø 10 m |
| Field of detection | up to 175 m² |
| Range adjustment | mechanically by tilting the motion detector head max 60° |
| Recommended installation height | 2.5 m |
| Max. mounting height | 2.5 m |
| Light measurement | mixed light |
| Level of brightness | 3 - 2000 lx |
| CHANNELS (LIGHTING / HVAC) | |
| Number of light channels | 1 |
| Push button input HVAC | 4 |
| Number of parallel switchable detectors | 8 |
| Slave input | _ |
| Switching delay from "dark to light" | 0 s |
| Switching delay from "light to dark" | 0 s |
| Constant light control | _ |
| Channel | C1 Lighting |
| Function | Switching |
| Switching capacity | 230 V/50 Hz |
| | 1000 W/4,5 A (cos phi = 1) 500 VA/2,25 A (cos phi = 0,5) 250 W LED |
| Switch contact | make contact / non-floating |
| Push button input | - |
| | |

DATA SHEET



MD 200 brown

Item number

GTIN

EM10025327

4015120025327

Impulse mode

Switch-off delay time

4 s...10 min (adjustable in steps)

Factory settings

GENERAL

Sensitivity 100 %

CHANNELS (LIGHTING / HVAC)

| Channel | C1 Lighting |
|----------------|-----------------|
| Operating mode | fully automatic |

Accessories

| Product designation | Item number | Product description | GTIN |
|------------------------|-------------|---|---------------|
| Electrical accessories | | | |
| FILTER 230 V | EP10426988 | Filter for suppression of inductive loads, such as relays, contactors, fluorescent lamps and transformers | 4015120426988 |
| Mounting | | | |
| MD EDGE MOUNTING BN | EM10025525 | Corner bracket for MD series, brown | 4015120025525 |

Dimension drawing

Field of detections

Detection range

Diagonally (A)

Ø 20 m

Frontal (B)

Ø 10 m

DATA SHEET





MD 200 brown

Item number GTIN

EM10025327 4015120025327

Circuit diagram Circuit diagram







Standard operation parallel connection of max. 8 devices

An RC filter may be required when connecting inductors (e.g. relays, contactors, ballasts).

Circuit diagram Circuit diagram





Standard operation with additional continuous lighting function through external switch.

Parallel connection with automatic stairwell light.

Detailed product description

- Motion detector with 200° field of detection for convenient light switching
- One-handed plug-base installation for quick and easy installation
- Double diaphragm line entry
- Connector bracket with large wiring space and optional line entrance from the top, bottom or rear
- Plug-in terminal for through-wiring of the protective conductor included
- · Sensing and range adjustment due to revolving and tilting spherical head technology
- Zero-cross switching: Extension of the lifetime of relays and illuminants with electronic ballasts (e.g. fluorescent lamps, LEDs) thanks to more gentle zero-cross switching
- For wall mounting
- Special bracket for mounting on inner and outer corners, available as accessory